# model EU-9001.5

Emergency Alarm System

## FEATURES & BENEFITS

**AUDIBLE/VISUAL**

Notification of an emergency is clearly noticeable with a brightly flashing amber light, and easily recognizable with a 90 db buzzer. Buzzer can be silenced during testing by use of the siliencing switch.

**FLOW SWITCH**

The alarm is activated by a 1/2" IPS brass double pole, double throw flow switch that is supplied with an extra set of electrical contacts for remote alarm hook-up.

**FLEXIBILITY**

The alarm is easily placed in a number of mounting configurations with the supplied pipe clamp.

## OPTIONS

For more information, visit www.hawsco.com or call (888) 640-4297.

## SPECIFICATIONS

Model 9001.5 emergency alarm and light system shall include an amber flashing light, and 90 db buzzer at 10 feet (304.8 cm) that is operated by a 1/2" NPT double pole, double throw flow switch which contains multiple sets of contacts for remote activation, and pipe bracket. Switch will activate at 1.5 gpm (3.8 L). Voltage: 120 VAC, 50 or 60 cycles. Supply: 1/2" IPS. Model 9001.5 is CSA electrical certified, TYPE 4. (Equivalent to Nema 4)

## APPLICATIONS

Specifically, this alarm can be used with almost any Haws eye or eye/face wash model. The complete alarm is CSA electrical certified, TYPE 4. (Nema 4 equivalent)


DISCLAIMER: Continued product improvements make specifications subject to change without notice. Check www.hawsco.com for the latest product information and updates.